

JPA 1120 Mixer Amplifier - 120W rms ac/dc Modular



A versatile mixer amplifier with five balanced inputs for four MIC1-4 and one AUX, or MIC1 and four AUX, each with volume control and chime or siren. Designed to accommodate any of the optional range of modules. 240Vac/24Vdc.

Also available in 30W (JPA 1030) and 60W (JPA 1060) versions.

Technical Specification

Power Output rms	120W
AC Power	50Hz 240V 50Hz
DC Power	24V
THD at rated power	<1%
Loudspeaker Outputs	100V, 70V / 4ohm, 8ohm
Frequency Response	70Hz - 20kHz
Mic Inputs	3mV / 600ohm
Aux Inputs	300mV / 50k ohm
Signal/Noise ratio, Mics	>60dB
Signal/Noise ratio, Aux	>70dB
Bass Control	±10dB at 100Hz
Treble Control	±10dB at 10kHz
Dimensions	H110 x W420 x D320 mm
Weight	12kg
Rack Mount Kit	10-0412-145

Product Code : 10-0402-C07