

JPA 1240 Mixer Amplifier - 240W rms ac/dc Modular



A mixer amplifier with 5 balanced microphone or line inputs. Features include

- * Each input equipped with a combination socket to accept both XLR and 6.35mm jack plugs
- * Inputs 1 and 2 have phantom power and priority assignment
- * Four separate output zones can be switched independently using front panel controls
- * Remote and direct chime
- * Two band graphic equalizer
- * External 24Vdc input
- * Rack mountable.

Technical Specification

Power Output rms	240W
AC Power	240V, 50Hz
DC Power	24V
THD at rated power	<6%
Loudspeaker Outputs	100V, 70V / 8ohm, 2.6ohm
Frequency Response	80Hz - 15kHz
Mic Inputs	2.45mV
Aux Inputs	245mV
Signal/Noise ratio, Mic	>60dB
Signal/Noise ratio, Aux	>70dB
Dimensions	H133 x W483 x D350 mm
Weight	13kg

Product Code : 10-6208-C07